This member provides a cross-reference index for each Output Master
V1R4M1 component that was modified by an optional USERMOD.

****

PLEASE NOTE THAT OUTPUT MASTER V1R4M1 IS AT FIX LEVEL OM14014 BASE.

****

Fix Number	Function
UMOD000	OPTIONAL. This usermod provides a bypass to a problem caused by entering the JES2 $SPRT command. The command causes the printer to interrupt at the end of printing the current dataset. When issued during the printing of the last output dataset, the command appears to function as desired. THIS USERMOD HAS RECEIVED LIMITED TESTING AT XENOS. DO NOT APPLY THIS MAINTENANCE AGAINST THE PRODUCTION VERSION OF THE HASPFSSM MODULE. INSTEAD, MAINTAIN A COPY IN A PRIVATE LIBRARY AND PLACE THE UPDATED VERSION INTO THE OUTPUT-MASTER LOAD LIBRARY. THE ENHANCED VERSION WILL BE LOADED DURING OUTPUT-MASTER INITIALIZATION AND CAN BE SUBSEQUENTLY DELETED WHEN THE IBM RESOLUTION IS MADE AVAILABLE. IEBUPDTE TO HASPFSSM. ** ** MODULES ** HASPFSSM ** MACROS ** ** PREREQS ** **

UMOD001	OPTIONAL. During normal processing, OUTPUT-Master uses the banner page to reset the JDE for 00122002 requests generated by OUTPUT-Master. This zap to 00122002 csect X97FSEPR in module X97FSEPR will add 00123003 "JDE=" and "JDL=" to the generated DJDE for 00123003 banner pages only when "DJDE=NO" processing is 00124003 requested. 00125002 ** ** MODULES ** X97FSEPR/X97FSEPR ** MACROS ** ** PREREQS ** None. **

UMOD002	OPTIONAL. This zap to csect X97FSERV in module X97FSERV is an extension to UMOD001. 00122001 00123001 Flip OUTPUT-Master into a "DJDE(NO)" type 00124001 process when the user has the DJDE font-indexed, 00124001 dependant on whether or not it contains a user 00125001 DJDE. 00126001 ** ** MODULES ** X97FSERV/X97FSERV **

MACROS ** **
PREREQS ** UMOD001 **

UMOD003 OPTIONAL. This zap to csect XDEVTEST in module
XDEVTEST removes the wait of a half second 00121000
between each print line when using the XDEVTEST 00121300
module instead of XDEVBSAM/X97FBSAM for testing. 00121401
** **
MODULES ** XDEVTEST/XDEVTEST **
MACROS ** **
PREREQS ** None. **

UMOD004 OPTIONAL. Suppresses form setup message and
eliminates requirement for operator to press 00121000
'CONTINUE' or 'ENTER' for printing to resume. 00121300
** **
MODULES ** X97FDJDE/X97FDHDE **
MACROS ** **
PREREQS ** None. **

UMOD005 OPTIONAL. Stop suppression of leading zero '0'
in year field of default banner page. Present
dates in the format '#d mon yy'.
Negative Impacts: Format #y will not be usable
after the zap is applied.
** **
MODULES ** XDEVSEPR/XDEVSEPR **
** X97FSEPR/X97FSEPR **
MACROS ** **
PREREQS ** None. **